



VHF AND UHF TRANSCEIVERS

IC-F1000T

VHF transceiver with full keypad

IC-F1000S

VHF transceiver with simple keypad

IC-F1000

VHF transceiver without LCD and front keypad

IC-F2000T

UHF transceiver with full keypad

IC-F2000S

UHF transceiver with simple keypad

IC-F2000

UHF transceiver without LCD and front keypad

Compact, Slim Dimensions IP67 Waterproofing and Full of Useful Features

IP67 Waterproof and Dust-tight Protection

The IC-F1000 series has a 24.5mm slim depth with IP67 waterproof casing. The transceiver can withstand 1m depth of water for 30 minutes. Its dust-tight construction prevents the ingress of powder dust, sand, mud and other objects.

Enhanced Emergency with Built-in Motion Sensor

With a built-in motion sensor, the IC-F1000 series can detect its position, state of motion and non-motion and can send an emergency signal. The motion function detects if the transceiver is moving or shaking, for example, during a chase. The lone worker and man down functions are programmable.

Easy to Hear in a Noisy Environment

The large 36mm speaker of the transceiver provides clear companded 800 mW* audio. The built-in BTL amplifier doubles the audio output power and delivers loud and intelligible voice to a radio operator working in noisy environments.

* Typical with internal speaker

Inversion Voice Scrambler

The built-in inversion voice scrambler provides secure conversation. Up to 16 codes are selectable.

14 Hours of Operating Time with Supplied Waterproof Battery

The supplied waterproof Li-Ion battery pack, BP-279 (7.2V DC, 1485mAh), provides 14 hours* of operating time.

* Tx:Rx:Standby=5:5:90. Power save function ON.

Quiet Stand-by and More

The IC-F1000 series has built-in 2-Tone, 5-Tone, CTCSS and DTCS signaling capabilities for group communication and selective calling.

MDC 1200 Compatible

The following MDC features are programmable.

- PTT ID • Emergency (No ACK transmission)
- Radio check (RX only) • Stun/Revive (RX only)
- Transmit status messages (LCD types only)
- 100 alias table (LCD types only)

Channel Announcement

When you rotate the channel knob, the radio announces the channel number. Convenient for making radio adjustments without having to look at the radio.

Other Features

- 8 DTMF autodial memories
- BIIS PTT ID and emergency call
- "Shift key" function increases number of programmable key assignments
- Surveillance function • Escalating alarm
- Optional HM-168LWP, waterproof speaker-mic



IC-F2000T

IC-F1000
(with optional stubby antenna)



Limited functions.

VHF AND UHF TRANSCEIVERS IC-F1000/T/S • IC-F2000/T/S

SPECIFICATIONS

| | IC-F1000/S/T | IC-F2000/S/T |
|--|---|---|
| GENERAL | | |
| Frequency coverage | 136–174MHz | 335–400MHz (EXP), 400–470MHz (EXP/EUR), 450–520MHz (EXP) |
| Number of channels | IC-F1000/F2000 IC-F1000T/S, F2000T/S | 16 channels 128 channels |
| Type of emission | EXP EUR | 16K0F3E/11K0F3E (25/12.5kHz) 16K0F3E/14K0F3E/11K0F3E (25/20/12.5kHz) |
| Power supply requirement | 7.5V DC | |
| Current drain (typical) | | |
| Tx High | 1.3A | 1.3A |
| Rx Max. audio/Standby | 330mA (Internal SP)/77mA | 300mA (Internal SP)/80mA |
| Antenna impedance | 50Ω | |
| Operating temperature range | EXP EUR –30°C to +60°C (Radio only) –25°C to +55°C (Radio only) | |
| Dimensions (W×H×D) (Projections not included) | 52.2×111.8×24.5mm (With BP-279) | |
| Weight (approx.) | 240g (With BP-279) | |
| TRANSMITTER | | |
| Output power (at 7.2V DC) | 5W, 2W, 1W (Hi, L2, L1) | 4W, 2W, 1W (Hi, L2, L1) |
| Max. frequency deviation | ± 5.0kHz/±4.0kHz/±2.5kHz (Wide/Middle/Narrow) | |
| Frequency stability | ±2.5ppm | |
| Spurious emissions | EXP EUR 70dB min. 0.25μW (≤ 1GHz), 1.0μW (> 1GHz) | |
| FM Hum and noise | EXP EUR 46/40dB typ. (Wide/Narrow, without CCITT filter) | |
| Residual modulations | EUR 45/43/40dB min. (W/M/N, with CCITT filter) | |
| Audio harmonic distortion (AF 1kHz 40% deviation) | 1.0%/1.0%/1.5% typ. (Wide/Middle/Narrow) | |
| Ext. microphone connector | 3-conductor 2.5 (d) mm (1/10")/2.2kΩ | |
| RECEIVER | | |
| Sensitivity | EXP EUR 0.25μV typ. (at 12dB SINAD) –4dBμV typ. emf (at 20dB SINAD) | |
| Adjacent channel selectivity | 70/70/40dB min. (Wide/Middle/Narrow) | |
| Spurious response | 70dB min. | |
| Intermodulation | EXP EUR 74dB typ. 65dB min. | |
| Hum and noise | EXP (With CCITT filter) EUR (Without CCITT) 51/45dB typ. (W/N) 45/43/40dB min. (W/M/N) | |
| Audio output power | Internal SP (With 12Ω load) External SP (With 8Ω load) 800mW typ. (at 5% distortion) 400mW typ. (at 5% distortion) | |
| Ext. speaker connector | 2-conductor 3.5 (d) mm (1/8")/8Ω | |

Measurements made in accordance with EN 300-086 (EUR) or TIA-603 (EXP). All stated specifications are subject to change without notice or obligation.

Applicable U.S. Military Specifications & IP Rating

| Standard | MIL 810G | |
|-------------------|----------|-----------|
| | Method | Procedure |
| Low Pressure | 500.5 | I, II |
| High Temperature | 501.5 | I, II |
| Low Temperature | 502.5 | I, II |
| Temperature Shock | 503.5 | I-C |
| Solar Radiation | 505.5 | I |
| Rain Blowing/Drip | 506.5 | I, III |
| Humidity | 507.5 | II |
| Salt Fog | 509.5 | – |
| Dust Blowing | 510.5 | I |
| Immersion | 512.5 | I |
| Vibration | 514.6 | I |
| Shock | 516.6 | I, IV |

Also meets equivalent MIL-STD-810-C, -D, -E and -F.

Ingress Protection Standard

| | |
|--------------|---|
| Dust & Water | IP67 (Dust-tight and waterproof protection) |
|--------------|---|

OPTIONS


Some options may not be available in some countries. Please ask your dealer for details.



| Battery packs | Type and capacity | Operating time* |
|---------------|-------------------------|-----------------------|
| BP-278 | Li-Ion, 7.2V 1130mAh | 10 hours (Approx.) |
| BP-279 | Li-Ion, 7.2V 1485mAh | 14 hours (Approx.) |


* Tx: Rx: standby = 5:5:90. Power save function ON.

RAPID CHARGER



Charges the BP-279 in 2.5 hours (approx.).

MULTI-CHARGER



Charges up to six BP-279 battery packs in 2.5 hours (approx.).

CIGARETTE LIGHTER CABLE & POWER SUPPLY CABLE



For use with BC-213
For use with BC-214

*1 BC-123SA for 120V AC. SE for 230V AC. SV for 240V AC.

SPEAKER-MICROPHONES



EARPHONE-MICROPHONES




HEADSETS



HS-94 Earhook type
HS-95 Behind-the-head type
HS-97 Throat type

PTT SWITCH CABLE



* VS-4LA is required when using the HS-94, HS-95 and HS-97.

BELT CLIP



Same as supplied.

CHARGER BRACKET



For use with BC-213

STANDARD ANTENNAS

- FA-SC25V : 136–150MHz
- FA-SC55V : 150–174MHz
- FA-SC25U : 400–430MHz
- FA-SC57U : 430–470MHz
- FA-SC72U : 470–520MHz

CUT ANTENNAS

- FA-SC61VC : 136–174MHz
- FA-SC61UC : 380–520MHz

HIGH GAIN ANTENNAS

- FA-SC62V : 150–160MHz
- FA-SC63V : 155–165MHz

STUBBY ANTENNAS

- FA-SC56VS : 150–162MHz
- FA-SC57VS : 160–174MHz
- FA-SC73US : 450–490MHz

CHARGER ADAPTER

- AD-130
AD-130 charger adapter is supplied with the BC-214.

Supplied accessories: (May differ depending on version)

- Battery pack, BP-279
- Desktop charger, BC-213
- AC adapter, BC-123S
- Belt clip, MB-133
- Antenna



The "3D GENUINE Icom label" is attached to the rear chassis under the battery. Check the Icom website for details: <http://www.icom.co.jp/world/genuine-info/>

Icom, Icom Inc. and the Icom logo are registered trademarks of Icom Incorporated (Japan) in the United States, the United Kingdom, Germany, France, Spain, Russia, Japan and/or other countries. All trademarks are the properties of their respective holders.

Icom Inc. 1-1-32, Kami-minami, Hirano-ku, Osaka 547-0003, Japan Phone: +81 (06) 6793 5302 Fax: +81 (06) 6793 0013

www.icom.co.jp/world

Count on us!

Icom America Inc.

12421 Willows Road NE,
Kirkland, WA 98034, U.S.A.
Phone : +1 (425) 454-8155
Fax : +1 (425) 454-1509
E-mail : sales@icomamerica.com
URL : <http://www.icomamerica.com>

Icom Canada

Glenwood Centre #150-6165 Highway 17,
Delta, B.C., V4K 5B8, Canada
Phone : +1 (604) 952-4266
Fax : +1 (604) 952-0090
E-mail : info@icomcanada.com
URL : <http://www.icomcanada.com>

Icom Brazil

Rua Itooró, 444 Padre Eustáquio
Belo Horizonte MG,
CEP: 30130-150, Brazil
Phone : +55 (31) 3582 8847
Fax : +55 (31) 3582 8987
E-mail : sales@icombrasil.com

Icom (Europe) GmbH

Communication Equipment
Auf der Krautweide 24
65812 Bad Soden am Taunus, Germany
Phone : +49 (6196) 76685-0
Fax : +49 (6196) 76685-50
E-mail : info@icom-europe.com
URL : <http://www.icomeurope.com>

Icom Spain S.L.

Ctra. Rubi, No. 88 "Edificio Can Castanyer"
Bajos A 08174, Sant Cugat del Valles,
Barcelona, Spain
Phone : +34 (93) 590 26 70
Fax : +34 (93) 589 04 46
E-mail : icom@icomspain.com
URL : <http://www.icomspain.com>

Icom Polska Sp. z o.o.

80-286 Gdansk, Jaskowa Dolina St. 75, Poland
Phone : +48 (58) 551 0484
Fax : +48 (58) 551 4720
E-mail : icompolska@icompolska.com.pl
URL : <http://www.icompolska.com.pl>

Icom (UK) Ltd.

Blacksole House, Altira Park,
Herne Bay, Kent, CT6 6GZ, U.K.
Phone : +44 (0) 1227 741741
Fax : +44 (0) 1227 741742
E-mail : info@icomuk.co.uk
URL : <http://www.icomuk.co.uk>

Icom France s.a.s.

Zac de la Plaine,
1 Rue Bréjondez des Moulinais, BP 45804,
31505 Toulouse Cedex 5, France
Phone : +33 (5) 61 36 03 03
Fax : +33 (5) 61 36 03 00
E-mail : icom@icom-france.com
URL : <http://www.icom-france.com>

Icom (Australia) Pty. Ltd.

Unit 1 / 103 Garden Road,
Clayton, VIC 3168 Australia
Phone : +61 (03) 9549 7500
Fax : +61 (03) 9549 7505
E-mail : sales@icom.net.au
URL : <http://www.icom.net.au>

Icom New Zealand

146A Harris Road, East Tamaki,
Auckland, New Zealand
Phone : +64 (09) 274 4062
Fax : +64 (09) 274 4708
E-mail : inquiries@icom.co.nz
URL : <http://www.icom.co.nz>

Asia Icom Inc.

6F No. 68, Sec. 1 Cheng-Teh Road,
Taipei, Taiwan, R.O.C.
Phone : +886 (02) 2559 1899
Fax : +886 (02) 2559 1874
E-mail : sales@asia-icom.com
URL : <http://www.asia-icom.com>

Shanghai Icom Ltd.

No. 101, Building 9, Caifuxingyuan Park,
No. 188 Maoting Road, Chedun Town,
Songjiang District, Shanghai, 201611, China
Phone : +86 (021) 6153 2768
Fax : +86 (021) 5765 9987
E-mail : bjicom@bjicom.com
URL : <http://www.bjicom.com>

Your local distributor/dealer: